

Nights with Alice Cooper/HardDriveXL Program-Associated Data

PAD/RDS information is available on the “PAD” serial port on PRO1/PRO4 receivers.

PAD/ASYNC Serial Port Pinouts

PRO1 Receivers

Pin	Function
1	P0_TX
2	N/C
3	N/C
4	N/C
5	N/C
6	Ground
7	Ground
8	Ground
9	Ground

PRO4 Receivers

Pin	Function
1	P0_TX
2	P1_TX
3	P2_TX
4	P3_TX
5	N/C
6	Ground
7	Ground
8	Ground
9	Ground

Settings for data are 9600, 8, N, 1

Station must use the proper pin for the audio port on which they take the program (Applies to PRO4 receivers only. PRO1 receivers should always output to pin 1)

PAD Format

ARTIST~TITLE~TIME (HH:MM:SS)

Followed by a carriage return

Data Output Example (three songs):

TOOL~STINKFIST~00:05:08

FIVE FINGER DEATH PUNCH~BAD COMPANY~00:04:20

KILLSWITCH ENGAGE~HOLY DIVER~00:04:08

The song time should be used for the station to return to a default/generic message upon completion of the current song.